

UNI-6 default midi implementation

Relay 1 - TIP 1 - DIN8 (pin 6)

Relay 2 - RING 1 - DIN8 (pin 4)

Relay 3 - TIP 2 - DIN8 (pin 8)

Relay 4 - RING 2 - DIN8 (pin 5)

Relay 5 - TIP 3 - DIN8 (pin 7)

Relay 6 - RING 3 - DIN8 (pin 3)

Common ground - All sleeves , DIN8 (pin2)

Rel1 [T1]	Rel2 [R1]	Rel3 [T2]	Rel4 [R2]	Rel5 [T3]	Rel6 [R3]	PC
TRS 1 (black dot marked)		TRS 2		TRS 3		
○	○	○	○	○	○	0
●	○	○	○	○	○	1
○	●	○	○	○	○	2
●	●	○	○	○	○	3
○	○	●	○	○	○	4
●	○	●	○	○	○	5
○	●	●	○	○	○	6
●	●	●	○	○	○	7
○	○	○	●	○	○	8
●	○	○	●	○	○	9
○	●	○	●	○	○	10
●	●	○	●	○	○	11
○	○	●	●	○	○	12
●	○	●	●	○	○	13
○	●	●	●	○	○	14
●	●	●	●	○	○	15
○	○	○	○	●	○	16
●	○	○	○	●	○	17
○	●	○	○	●	○	18
●	●	○	○	●	○	19
○	○	●	○	●	○	20
●	○	●	○	●	○	21
○	●	●	○	●	○	22
●	●	●	○	●	○	23
○	○	○	●	●	○	24
●	○	○	●	●	○	25
○	●	○	●	●	○	26
●	●	○	●	●	○	27
○	○	●	●	●	○	28
●	○	●	●	●	○	29
○	●	●	●	●	○	30
●	●	●	●	●	○	31
○	○	○	○	○	●	32
●	○	○	○	○	●	33
○	●	○	○	○	●	34
●	●	○	○	○	●	35
○	○	●	○	○	●	36

●	○	●	○	○	●	37
○	●	●	○	○	●	38
●	●	●	○	○	●	39
○	○	○	●	○	●	40
●	○	○	●	○	●	41
○	●	○	●	○	●	42
●	●	○	●	○	●	43
○	○	●	●	○	●	44
●	○	●	●	○	●	45
○	●	●	●	○	●	46
●	●	●	●	○	●	47
○	○	○	○	●	●	48
●	○	○	○	●	●	49
○	●	○	○	●	●	50
●	●	○	○	●	●	51
○	○	●	○	●	●	52
●	○	●	○	●	●	53
○	●	●	○	●	●	54
●	●	●	○	●	●	55
○	○	○	●	●	●	56
●	○	○	●	●	●	57
○	●	○	●	●	●	58
●	●	○	●	●	●	59
○	○	●	●	●	●	60
●	○	●	●	●	●	61
○	●	●	●	●	●	62
●	●	●	●	●	●	63

CONTROL CHANGE switching

Function	CC number	CC value	
		0 - 62	64 - 127
Rel1	80	○	●
Rel2	81	○	●
Rel3	82	○	●
Rel4	83	○	●
Rel5	84	○	●
Rel6	85	○	●

63 -> toggle